

0.8mm Height 0603 Package Prue Green Chip LED Technical Data Sheet

Part No :LL-S190PGC-G5-1B





Features

- ◇ Package in 8mm tape on 7" diameter reel.
- ♦ Compatible with automatic lacement equipment.
- ◇ Compatible with infrared and vapor phase reflow solder process.
- ♦ Mono-color type.
- ◇ Pb-Free.
- ♦ The product itself will remain within RoHS compliant Version.

Descriptions

- The S190 SMD LED is much smaller than lead frame type Components, thus enable smaller board size, higher packing Density, reduced storage space and finally smaller equipment to be obtained.
- ♦ Besides, lightweight makes them ideal for miniature applications.etc.

Applications

- ♦ Automotive:backlighting in dashboard and switch.
- Telecommunication:indicator and backlighting in Telephone and fax.
- ♦ Flat backlight for LCD, switch and symbol.
- ♦ General use.





Rev No:V.1 Spec No: G010/G008PG Approved: Zhan Checked: Bob Lucky Light Electronics Co., Ltd



Absolute Maximum Ratings at Ta=25℃

Parameter	Symbol	MAX	Unit
Power Dissipation	PD	100	mW
Peak Forward Current (1/10 Duty Cycle, 0.1ms Pulse Width)	IFP	70	mA
Continuous Forward Current	IF	25	mA
Reverse Voltage	VR	5	V
Electrostatic Discharge	ESD	150 V	
Operating Temperature Range	Topr	-40℃ to +85℃	
Storage Temperature Range	Tstg	-40°℃ to +90°℃	
Soldering Temperature	Tsld	260℃ for 5 Seconds	

Electrical Optical Characteristics at Ta=25°C

Parameter	Symbol	Min.	Тур.	Max.	Unit	Test Condition
Viewing Angle*	2 θ 1/2	100	120	140	Deg	(Note 2)
Forward Voltage	VF		3.5	4.0	V	IF =20mA
Reverse Current	IR			10	μA	V _R =5V
Peak Emission Wavelength	λp	513	518	523	nm	IF=20mA
Dominant Wavelength	λ d	520	525	530	nm	IF=20mA (Note 3)
Spectral Line Half-Width	$\bigtriangleup \lambda$	25	30	35	nm	IF=20mA
Luminous Intensity (Note 1)*	lv	95	145		mcd	IF =20mA

1. Luminous Intensity Measurement allowance is $\pm 10\%$

2. $\theta_{1/2}$ is the off-axis angle at which the luminous intensity is half the axial luminous intensity



Reliability Test Items And Conditions

The reliability of products shall be satisfied with items listed below.

Confidence level:90%

LTPD:10%

1)Test Items and Results

No.	Test Item	Test Hours/C ycles	Test Conditions	Sample Size	Ac/Re
1	Resistance to Soldering Heat	6 Min	Tsld=260±5℃, Min. 5sec	25pcs	0/1
2	Themal Shock	300 Cycles	H:+100℃ 5min ∫ 10 sec L:-10℃ 5min	25pcs	0/1
3	Temperature Cycle	300 Cycles	H:+100℃ 15min ∫ 5min L:-40℃ 15min	25pcs	0/1
4	High Temperature Storage	1000Hrs.	Temp:100 ℃	25pcs	0/1
5	DC Operating Life	1000Hrs.	lf=20mA	25pcs	0/1
6	Low Temperature Storage	1000Hrs.	Temp:-40 ℃	25pcs	0/1
7	High Temperature/ High Humidity	1000Hrs.	85℃/85%RH	25pcs	0/1

2)Critera For Judning The Damage

Item Symbl Test Conditions		Criteria for Judgement		
			Min	Max
Forward Voltage	VF	l⊧=20mA		F.V.*)×1.1
Reverse Current	IR	VR=5V		F.V.*)×2.0
Luminous	IV	l⊧=20mA	F.V.*)×0.7	_

*)F.V.:First Value





Lucky Light Electronics Co., Ltd

Http://www.luckylight.cn





Lucky Light Electronics Co., Ltd

Http://www.luckylight.cn



Please read the following notes before using the datasheets

1. Over-current-proof

Customer must apply resistors for protection , otherwise slight voltage shift will cause big current change (Burn out will happen).

2. Storage

2.1 Do not open moisture proof bag before the products are ready to use.

2.2 Before opening the package, the LEDs should be kept at 30° C or less and 90%RH or less.

- 2.3 The LEDs should be used within a year.
- 2.4 After opening the package, the LEDs should be kept at 30 $^\circ\!C$ $\,$ or less and 70%RH or less.
- 2.5 The LEDs should be used within 168 hours (7 days) after opening the package.
- 2.6 If the moisture adsorbent material (silica gel)has fabed away or the LEDs have exceeded the storage time,baking treatment should be performed using the following conditions. Baking treatment:60±5°C for 24 hours.

3. Soldering Condition

3.1 Pb-free solder temperature profile



3.2 Reflow soldering should not be done more than two times.

3.3 When soldering, do not put stress on the LEDs during heating.

3.4 After soldering, do not warp the circuit board.

4. Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than 260° C for 5 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering

of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

Spec No: G010/G008PGRev No:V.1Approved:ZhanChecked:BobLucky Light Electronics Co., Ltd



5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand

whether the characteristics of the LEDs will or will not be damaged by repairing.



6. Caution in ESD:

Siatic Electricity and surge damages the LED. It is recommend to use a wrist band or anti-electrostatic glove when handling the LED.All devices, equipment and machinery must be properly grounded.